



	Liczba skrzydeł n / Quantity of doors n	n = 2	n = 3	n = 4	n = 5	n = 6	n = 7	n = 8
	Wysokość płyty hP [mm] / Board height hP [mm]	$hP = H - 42$ ($hP = H - 44$)*						
Szerokość płyty bP [mm] / Board width bP [mm]	$bP = (S + 18) / 2$	$bP = (S + 40) / 3$	$bP = (S + 56) / 4$	$bP = (S + 76) / 5$	$bP = (S + 94) / 6$	$bP = (S + 114) / 7$	$bP = (S + 132) / 8$	
Wysokość lustra hL [mm] / Mirror height hL [mm]	$hL = H - 43$ ($hL = H - 45$)*							
Szerokość lustra bL [mm] / Mirror width bL [mm]	$bL = bP - 2$							
Długość ramiaków oraz łącznika R [mm] Upper, lower rail and connector length R [mm]	$R = bP - 32$							
Długość rączki LR [mm] / Handle length LR [mm]	$LR = H - 40$ ($LR = H - 42$)*							

* wersja z samodomykaczem / softcloser version







